
Single Stage Ferrite Circulator / Isolator 90-91 MHz

VHF UHF



JAG-IC-90-1-XX





JAG-IC-132-1-30 Shown with a 30W load

JAG isolators and circulators offer superior performance in a compact rugged package. Careful temperature compensation and top quality components ensure high isolation with very low insertion loss over their full operating temperature range, and offer a high degree of RF and magnetic stability. Circulators are supplied without loads. Isolators come equipped with a variety of load terminations. JAG isolators and circulators are available factory-tuned in the 70, 150, 450 and 800-960 MHz frequency bands. Field tunable isolators are available for the 138-174 and 406-430 or 450-470 MHz bands.

Electrical Specific	Mechanical Specifications				Environmental			
Model JAG-IC-90-1-XX	Model JAG-IC-90-1-XX				Model	JAG-IC-90-1-XX		
Frequency Range (MHz)	90-91	*Note 1	Height	inches (m	m)	3 (76.2)	Temperati	ure Range -40-degC to +60-degC
Bandwidth @ 1.3:1 VSWR or Bette	er (MHz)	2	Width	inches (m	m)	3 (76.2)	Notes:	
Maximum Input VSWR	1.3:1		Depth	inches (m	m)	1.4 (35)	frequency when ordering 2. Power rating for isolators and circulators is determined by load size	
Maximum Input Power (Watts)	125	*Note 2	Weight	lb (kg)	2.2 (1.0)	*No load		
Maximum Insertion Loss (dB)	1aximum Insertion Loss (dB) 0.7		Mounting Systems		19-inch rack mount	with a maximum going up to 125W 3. Typically 25-30dB of reverse isolation		
Typical Insertion Loss (dB)	0.4				Cavity Plate Cabinet Customized	may be observed 4. Replace the X in the model number as follows: • 0 = Circulator (no loads) • 15 = 15W load • 30 = 30W load	as follows:	
Isolation (dB)	22	*Note 3						
Nominal Impedance (Ω)	50		Termination		'N' Female			
Output Load Size (Watts)	15 30 60 125	*Note 4 *Note 4 *Note 4 *Note 4					 60 = 60W load 125 = 125W load Example: JAG-IC-90-1-60 (comes with a 60W load) 	

Dated: September-17-2014

Electromagnetics

JAG-IC-90-1-XX Product Specification Sheet.

This is a general representation of what the actual product may look like.

RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: <u>www.jagelectromagnetics.com</u> Tel (905)-635-7437 Fax (905)-332-8093

Made in Canada

Copyright © JAG Electromagnetics



JAG's dedication to continuous Research & Development will result in product improvements as they evolve.

Page 1/1

Rev091714.0

Specifications are subject to change without notice. As a result, all information contained in the present datasheet is subject to confirmation at time of ordering.