

ISLI Series Single Stage Coaxial UHF Isolator 156-174 MHz

## JAG-IS1-156-174-N10-X



JAG coaxial isolators offer excellent performance in a compact rugged package. Quality components ensure good isolation with low insertion loss over their full operating temperature range. These isolators come equipped with a variety of load terminations. JAG ISLI series coaxial isolators offer a broad selection of frequency ranges and bandwidth from 132MHz-18GHz and from 1% to full bandwidth. Applications of these isolators range from military to space to commercial and are available in high power versions with connector options from N type to SMA. Other options available are integral attenuators and custom designs.

Electrical Specific	Mechanical Specifications				Environmental				
Model JAG-IS1-156-17	Model JAG-IS1-156-174-N10-X			110-X	Model	JAG-IS1-156-174-N10-X			
Frequency Range (MHz)	156-174	*Note 1	Height	inches (mr	n)	2.75 (70)	Temperatu	re Range 0-degC to +60-degC	
Bandwidth @ 1.4:1 VSWR or Bet	er (MHz)	18	Width	inches (mr	n)	2.75 (70)	Notes:	Chaolify model number and event	
Maximum Input VSWR	1.4:1		Depth	inches (mr	n)	0.875 (22)	1.	Specify model number and exact frequency when ordering	
Maximum FWD Input Power (Watts) 150			Weight	lb (kg)		2 (0.91)	2.	Reverse power ratings for isolators are determined by load size with a	
Maximum REV Input Power (Watts) 100			Mounting Systems 19-inch rack mount			mount	<ul><li>maximum going up to 100W</li><li>3. Replace the X in the model number</li></ul>		
Maximum Insertion Loss (dB)	0.7				Cavity Plate	•	for optional loads as follows: S = Standard load (default)		
Minimum Isolation (dB)	15	*Note 2			Cabinet Customized		<ul> <li>15 = 15W load</li> <li>30 = 30W load</li> <li>60 = 60W load</li> <li>100 = 100W load</li> </ul>		
Nominal Impedance (Ω)	50		Termination (default)		N-f				
Optional Load Sizes (Watts)	30 *Note 60 *Note	*Note 3		on (optional)	N-m/ SMA-f(m)		,		
1 ( )		*Note 3 *Note 3 *Note 3	Case Code		IC34		Example: JAG-IS1-156-174-N10-15 (comes with a 15W load)		


\* This is a general representation of what the actual product may look like.

Dated: September-17-2014

Issue: 1

RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada Email: info@jagelectromagnetics.com Web: www.jagelectromagnetics.com Tel (905)-635-7437 Fax (905)-332-8093 Made in Canada

Copyright © JAG Electromagnetics



JAG's dedication to continuous Research & Development will result in product improvements as they evolve. Specifications are subject to change without notice. As a result, all information contained in the present datasheet is subject to confirmation at time of ordering.