


ISLI Series Single Stage Coaxial UHF solator 300-420 MHz





JAG coaxial isolators offer excellent performance in a compact rugged package. Quality components ensure good isolation with low insertion loss over their full operating temperature range. These isolators come equipped with a variety of load terminations. JAG ISLI series coaxial isolators offer a broad selection of frequency ranges and bandwidth from 132MHz-18GHz and from 1% to full bandwidth. Applications of these isolators range from military to space to commercial and are available in high power versions with connector options from N type to SMA. Other options available are integral attenuators and custom designs.

Electrical Specific	Mechanical Specifications				Environmental					
Model JAG-IS1-300-42	Model	Model JAG-IS1-300-420-N10-X			Model JAG-IS1-300-420-N10-X					
Frequency Range (MHz)	300-420	*Note 1	Height	inches (mi	m) 3.3	5 (85)	Temperatu	ire Range	-30-degC to +60-degC	
Bandwidth @ 1.4:1 VSWR or Bet	ter (MHz)	120	Width	inches (mi	m) 2.0	5 (52)	Notes:			
Maximum Input VSWR	1.4:1		Depth	Depth inches (mm) 0.875 (22)		75 (22)	1. Specify model number and exact frequency when ordering			
Maximum FWD Input Power (Watts) 200		Weight	lb (kg)	2 (0).91)	2.	Reverse power ratings for isolators are determined by load size with a			
Maximum REV Input Power (Watts) 100			Mounting Systems		19-inch rack mount	maximum going up to 100W 3. Replace the X in the model number				
Maximum Insertion Loss (dB)	0.6				Cavity Plate		•	for optional loads as follows: S = Standard load (default)		
Minimum Isolation (dB)	15	*Note 2]		Cabinet Customized	•	15 = 15W load 30 = 30W load			
Nominal Impedance (Ω)	50		Termination (default)		N-f		 60 = 60W load 100 = 100W load 			
Optional Load Sizes (Watts)	15	*Note 3	Termination (optional)		N-m/ SMA-f(m)					
	30	*Note 3	Case Coo	de	IC02		Example: JAG-IS1-300-420-N10-15 (comes with a 15W load)			
	60 100	*Note 3 *Note 3								

* This is a general representation of what the actual product may look like.

Dated: September-17-2014



RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Issue: 1

Email: info@jagelectromagnetics.com Web: www.jagelectromagnetics.com Tel (905)-635-7437 Fax (905)-332-8093



Copyright © JAG Electromagnetics

Rev091714.0 Page 1/1

JAG's dedication to continuous Research & Development will result in product improvements as they evolve.

Specifications are subject to change without notice. As a result, all information contained in the present datasheet is subject to confirmation at time of ordering.