Single Stage Coaxial UHF Isolator

935-960 MHz

JAG-IS1-935-960-S10-X



JAG coaxial isolators offer excellent performance in a compact rugged package. Quality components ensure good isolation with low insertion loss over their full operating temperature range. These isolators come equipped with a variety of load terminations. JAG ISLI series coaxial isolators offer a broad selection of frequency ranges and bandwidth from 132MHz-18GHz and from 1% to full bandwidth. Applications of these isolators range from military to space to commercial and are available in high power versions with connector options from N type to SMA. Other options available are integral attenuators and custom designs.

| Electrical Specifications | | | Mechanical Specifications | | | Envir | Environmental | |
|-------------------------------------|-----------------------------|-------------------------------|---------------------------|------------|--|----------|---|--|
| Model JAG-IS1-935-960 | Model JAG-IS1-935-960-S10-X | | | Model | JAG-IS1-935-960-S10-X | | | |
| Frequency Range (MHz) | 935-960 | *Note 1 | Height | inches (mr | m) 2.36 (60) | Temperat | ture Range -30-degC to +75-degC | |
| Bandwidth @ 1.25:1 VSWR or Bet | ter (MHz) | 25 | Width | inches (mr | m) 1.38 (35) | Notes: | Specify model number and exact frequency when ordering | |
| Maximum Input VSWR | 1.25:1 | | Depth | inches (mr | m) 0.787 (20) | 1. | | |
| Maximum FWD Input Power (Watts) 150 | | Weight lb (kg) 2 (0.91) | | 2. | Reverse power ratings for isolators are determined by load size with a | | | |
| Maximum REV Input Power (Watts) 100 | | | Mounting Systems | | 19-inch rack mount | 3. | or replace the remaining model hamber | |
| Maximum Insertion Loss (dB) | 0.35 | | | | Cavity Plate Cabinet Customized | • | for optional loads as follows: S = Standard load (default) 15 = 15W load 30 = 30W load 60 = 60W load 100 = 100W load | |
| Minimum Isolation (dB) | 22 | *Note 2 | | | | • | | |
| Nominal Impedance (Ω) | 50 | | | | SMA-f N-f(m)/ SMA-m | | | |
| Optional Load Sizes (Watts) | 15 | *Note 3 | Termination (optional) | | | Fuerrale | Example: JAG-IS1-935-960-S10-15 (comes with a 15W load) | |
| , | 30 60 100 | *Note 3 *Note 3 *Note 3 | Case Code IC04 | | IC04 | | | |
| | | | | | | | ·, | |

Dated: September-17-2014

Electromagnetics

JAG-IS1-935-960-S10-X Product Specification Sheet.

Issue: 1

RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: www.jagelectromagnetics.com Tel (905)-635-7437 Fax (905)-332-8093 Made in Canada

Rev091714.0

Page 1/1



JAG's dedication to continuous Research & Development will result in product improvements as they evolve.

* This is a general representation of what the actual product may look like.

Specifications are subject to change without notice. As a result, all information contained in the present datasheet is subject to confirmation at time of ordering.