

**Delta1 Series** EXPOSED FOLDED UHF **DIPOLE 2-Bay Array** 195-245 MHz



JAG-220-2-1/2-SM





- Civil aviation applications
- Land mobile networks
- Public security and safety
- Transportation networks











	١
	F
	B V
	Р
sheet.	R
-1/2-SM Product Specification Sheet	N
	P R N
	N 3
7	

		Environmental  Model JAG-220-2-1/2-SM  Survival Wind Velocity With no Ice mph (km/h) 135 (217)  Survival Wind Velocity With Ice mph (km/h) 100 (161)  Maximum Allowable Radial Ice Buildup inches (mm) 0.5 (12.7)  Equivalent Flat Plate Area ft^2 (m^2) 2.1 (0.2)  Lateral thrust (100mph) 0 Radial Ice Buildup ft-lbs (Nm) 83 (112.1)  Bending moment (100mph) 0 Radial Ice Buildup ft-lbs (Nm) 247 (333.5)
Electrical Specifications	Mechanical Specifications	Environmental
Model JAG-220-2-1/2-SM	Model JAG-220-2-1/2-SM	Model JAG-220-2-1/2-SM
Frequency Range (MHz) 195 – 245	Height inches (mm) 65 (1,651)	Survival Wind Velocity With no Ice mph (km/h) 135 (217)
Bandwidth @ 1.5:1 VSWR or Better (MHz) 50	Width inches (mm) 36 (914.4)	Survival Wind Velocity
Polarization Vertical	Depth inches (mm) 4.25 (108)	With Ice mph (km/h) 100 (161)
Radiation Pattern Bi-directional (Elliptical)	Weight lb (kg) 22 (9.97)	Maximum Allowable Radial Ice Buildup inches (mm) 0.5 (12.7)
Nominal Gain (dBd) 3 – 3.7	Support Mast Outside Diameter Inches (mm) 2.375 (60.3)	Equivalent Flat Plate Area ft^2 (m^2) 2.1 (0.2)
Nominal Horizontal 3dB Beamwidth (Deg) 205 – 215	Support Mast	Lateral thrust (100mph)
Nominal Vertical 3dB Beamwidth (Deg) 33 – 35	Allowable Clamping Space Inches (mm) 15 (381)	0 Radial Ice Buildup lbs (N) 77 (342.5)  Torsional moment (100mph)
Maximum Average Power (Watts) 200	Mounting Information No clamps supplied (See JAG clamps page for suitable clamps)	0 Radial Ice Buildup ft-lbs (Nm) 83 (112.1)
Lightning Protection DC Ground	Pigtail (ft) & RF Connector 1 – 1.5 & 'N' Male	Bending moment (100mph) 0 Radial Ice Buildup ft-lbs (Nm) 247 (333.5)

Dated: February-20-2011



RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: <u>www.jagelectromagnetics.com</u> Tel (905)-635-7437 Fax (905)-332-8093

Made in Canada



JAG's dedication to continuous Research & Development will result in product improvements as they evolve.

Page 1/4

### **Delta1 Series**

# EXPOSED FOLDED VHF DIPOLE 2-Bay Array

195-245 MHz

JAG-220-2-1/2-SM

## **Features**

- 5-year factory warranty (See page 3)
- Broadband (50 MHz)
- Suitable for multi-frequency systems
- Medium gain applications
- Soldered internal joints
- DC Grounded
- Stainless steel hardware
- Small for easy transport and installation
- Fits in standard Otis Elevators
- Stock for re-use or re-sale
- Low PIM
- Operation in harsh environments
- Optional lightning rod spike
- Optional downtilt versions
- Optional inverted mountable model

- Side or tower top mountable
- Optional coatings
- Ideal for monitoring stations

### **Description**

The JAG-220-2-1/2-SM is a 2-bay version of the JAG-220-1-1/2, incorporating all the features of the basic model into a medium gain antenna needed in certain system applications. The JAG-220-2-1/2-SM is supplied with either quarter-wave (JAG-220-2-1/4-SM) or half-wave (JAG-220-2-1/2-SM) dipole-to-mast spacing. Site-specific mounting hardware is required with these antennas. Please consult JAG for suitable clamps.

The JAG-220-2-1/2-SM offers a short mast design (only 5.5-feet in length) to facilitate easy transport, rooftop access, and installation resulting in a cost effective antenna for urban sites.

Being an antenna from the Delta1 Series means the phasing harness is contained within the mast. This provides the added benefit of a protected harness compared to a situation where only an external harness antenna could traditionally be used (determined by antenna size and site accessibility).

Therefore, the JAG-220-2-1/2-SM gives you both maximum protection for the precision phasing harness and the small size needed to negotiate some sites.

The JAG-220-2-1/2-SM, with its rugged construction and ease of installation, is ideal for leased or rented system use. Its bandwidth also makes it perfect to stock for re-use or re-sale.

# JAG-220-2-1/2-SM at a glance



Expert TIG welding

JAG to determine suitable clamps for your application



Natural rubber plugs



Heavy-duty dipole fixture



Optional lightning rod



Site-specific mounting hardware is necessary with theses antennas. Please consult

RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: <u>www.jagelectromagnetics.com</u> Tel (905)-635-7437 Fax (905)-332-8093

Made in Canada



Copyright © JAG Electromagnetics


Rev022011.0

Page 2/4

JAG's dedication to continuous Research & Development will result in product improvements as they



JAG-220-2-1/2-SM



<sup>\*</sup> This is a general representation of the Delta1 Series JAG-220-2-1/2-SM antenna radiation pattern. For the latest detailed pattern contact JAG Applications Engineering.

### WARRANTY

JAG Electromagnetics warrants all its products against defects in material or workmanship and is only applicable if failure results from these factors within five years from the purchase date by the user. Jag Electromagnetics will be responsible for the supply, at no charge, of new or rebuilt replacements in exchange for defective parts for the duration of the warranty. This warranty does not extend to any JAG products that have been subject to misuse, neglect, accident, improper installation or application. In addition, this warranty does not extend to products that have been repaired or substantially altered outside our manufacturing plant.

JAG Electromagnetics will not be liable for any incidental or consequential damages due to failure of a JAG product under this warranty or any implied warranty. JAG is in no event liable for consequential damages or other costs of any kind as a result of the use of the products manufactured by JAG. No envoy is sanctioned to presume for JAG any other legal responsibility in connection with JAG products. JAG Electromagnetics is not accountable for replacement of any product damaged by lightning.

Dated: February-20-2011



Issue: 1

RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: www.jagelectromagnetics.com Tel (905)-635-7437 Fax (905)-332-8093 Made in Canada

\*

Copyright © JAG Electromagnetics


Rev022011.0

Page 3/4

JAG's dedication to continuous Research & Development will result in product improvements as they



JAG-220-2-1/2-SM



<sup>\*</sup> This is a general representation of the Delta1 Series JAG-220-2-1/2-SM antenna radiation pattern. For the latest detailed pattern contact JAG Applications Engineering.

#### Toronto:

JAG Electromagnetics 26-1750 Creek Way Burlington, ON, L7L 7E2 Canada Tel (905)-635-7437 Fax (905)-332-8093

Email: info@jagelectromagnetics.com

#### Saskatoon:

JAG Electromagnetics 30065-1624 33<sup>rd</sup> St. W Saskatoon, SK, S7L 7M6 Canada Tel (905)-635-7437 Fax (905)-332-8093

Email: info@jagelectromagnetics.com

Published by JAG and printed in Canada. This document cannot be printed or duplicated other than for its intended purpose as a JAG product selection guide without the written consent of JAG Electromagnetics.

Dated: February-20-2011

JAG-220-2-1/2-SM Product Specification Sheet.



Issue: 1

RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: www.jagelectromagnetics.com Tel (905)-635-7437 Fax (905)-332-8093 Made in Canada

Rev022011.0

Page 4/4



JAG's dedication to continuous Research & Development will result in product improvements as they evolve. Specifications are subject to change without notice. As a result, all information contained in the present datasheet is subject to confirmation at time of ordering