Delta1 Series EXPOSED FOLDED WHF **DIPOLE 2-Bay Array** 406-512 MHz



Electromagnetics "Quality is everything."



JAG-450-2-1/4-SM



- Civil aviation applications
- Land mobile networks
- Public security and safety
- Transportation networks











Electrical Specifications		Mechanical Specifications			Environmental	
Model JAG-450-2-1/4-SM		Model JAG-450-2-1/4-SM			Model JAG-450-2-1/4-SM	
Frequency Range (MHz)	406 – 512	Height	inches (mm)	60 (1,524)	Survival Wind Velocity With no Ice	mph (km/h) 175 (282)
Bandwidth @ 1.5:1		Width	inches (mm)	8 (203.2)		mpir (kirim) 173 (202)
VSWR or Better (MHz)	106	Depth	Depth inches (mm) 4.25 (108)		Survival Wind Velocity With Ice mph (km/h) 110 (177)	
Polarization	Vertical	Weight	lb (kg)	10 (4.5)	Maximum Allowable	
Radiation Pattern	Offset	Support Mast Outside Diameter		()	Radial Ice Buildup inches (mm) 0.5 (12.7)	
Nominal Gain (dBd)	3.7 – 4.2			2.375 (60.3)	Equivalent Flat Plate Area	ft^2 (m^2) 0.96 (0.09)
Nominal Horizontal						
3dB Beamwidth (Deg)	205 – 215		Support Mast Allowable Clamping Space		Lateral thrust (100mph) 0 Radial Ice Buildup	lbs (N) 38.5 (171.3)
Nominal Vertical	00 05		Inches (mm)	24 (609.6)	, , , , ,	
3dB Beamwidth (Deg)	33 – 35	Mounting	Information No clamps	s supplied*	Torsional moment (100 0 Radial Ice Buildup	mpn) ft-lbs (Nm) 11 (14.9)
Maximum Average Power (Watts)	200	*(See JAG clamps page for suitable clamps)			, , , , ,	
Lightning Protection	DC Ground	Pigtail (ft)	& RF Connector 2 – 2	2.5 & 'N' Male	Bending moment (100n 0 Radial Ice Buildup	nph) ft-lbs (Nm) 76.5 (103.3)

Dated: February-15-2011

JAG-450-2-1/4-SM Product Specification Sheet.



RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Fax (905)-332-8093

Made in Canada

Copyright © JAG Electromagnetics

JAG's dedication to continuous Research & Development will result in product improvements as they evolve.

Page 1/4

Rev021511.1

Specifications are subject to change without notice. As a result, all information contained in the present datasheet is subject to confirmation at time of ordering.

Delta1 Series

DIPOLE 2-Bay Array EXPOSED FOLDED VHF

406-512 MHz

JAG-450-2-1/4-SM

Electromagnetics "Quality is everything."

Features

- 2-year factory warranty (See page 3)
- Broadband (106 MHz)
- Suitable for multi-frequency systems
- Soldered internal joints
- Small for easy transport and installation
- Fits in standard Otis Elevators
- DC Grounded
- Stainless steel hardware
- Easy storage
- Low PIM
- Operation in harsh environments
- Optional lightning rod spike
- Optional downtilt versions
- Optional inverted mountable model
- Side or tower top mountable
- Optional coatings such as black paint

- Courier shippable
- Ideal for monitoring stations

Description

The JAG-450-2-1/4-SM is a 2-bay version of the JAG-450-1-1/4, incorporating all the features of the basic model into a medium gain antenna needed in certain system applications. The JAG-450-2-1/4-SM is supplied with either quarter-wave (JAG-450-2-1/4-SM) or half-wave (JAG-450-2-1/2-SM) dipole-to-mast spacing. Site-specific mounting hardware is required with these antennas. Please consult JAG for suitable clamps.

The JAG-450-2-1/4-SM offers a short mast design (only five feet in length) to facilitate easy transport, rooftop access, and installation resulting in a cost effective antenna for urban sites.

As a result of the antennas 5-foot compact design, it is shippable by most courier companies such as FedEx or UPS. This is much more convenient than traditional freight shipping required for comparable antennas

The JAG-450-2-1/4-SM, with its rugged construction, lightweight and ease of installation, is ideal for leased or rented system use. Its bandwidth also makes it perfect to stock for re-use or re-sale.





JAG-450-2-1/4-SM at a glance



Expert TIG welding



Natural rubber plugs



Heavy-duty dipole fixture



Optional lightning rod

*Site-specific mounting hardware is necessary with theses antennas. Please consult JAG to determine suitable clamps for your application

Dated: February-15-2011



RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: <u>www.jagelectromagnetics.com</u> Tel (905)-635-7437 Fax (905)-332-8093

Made in Canada



Copyright © JAG Electromagnetics

Rev021511.1


Page 2/4

JAG's dedication to continuous Research & Development will result in product improvements as they

Delta1 Series EXPOSED FOLDED WHF DIPOLE 2-Bay Array 406-512 MHz



JAG-450-2-1/4-SM



^{*} This is a general representation of the Delta0 Series JAG-450-2-1/4-SM antenna radiation pattern. For the latest detailed pattern contact JAG Applications Engineering.

WARRANTY

JAG Electronmagnetics warrants all its products against defects in material or workmanship and is only applicable if failure results from these factors within two years from the purchase date by the user. Jag Electromagnetics will be responsible for the supply, at no charge, of new or rebuilt replacements in exchange for defective parts for the duration of the warranty. This warranty does not extend to any JAG products that have been subject to misuse, neglect, accident, improper installation or application. In addition, this warranty does not extend to products that have been repaired or substantially altered outside our manufacturing plant.

JAG Electromagnetics will not be liable for any incidental or consequential damages due to failure of a JAG product under this warranty or any implied warranty. JAG is in no event liable for consequential damages or other costs of any kind as a result of the use of the products manufactured by JAG. No envoy is sanctioned to presume for JAG any other legal responsibility in connection with JAG products. JAG Electromagnetics is not accountable for replacement of any product damaged by lightning.

Dated: February-15-2011



Issue: 1

RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: www.jagelectromagnetics.com Tel (905)-635-7437 Fax (905)-332-8093 Made in Canada


Rev021511.2 Page 3/4



Specifications are subject to change without notice. As a result, all information contained in the present datasheet is subject to confirmation at time of ordering



JAG-450-2-1/4-SM



^{*} This is a general representation of the Delta0 Series JAG-450-2-1/4-SM antenna radiation pattern. For the latest detailed pattern contact JAG Applications Engineering.

Toronto:

JAG Electromagnetics 26-1750 Creek Way Burlington, ON, L7L 7E2 Canada Tel (905)-635-7437 Fax (905)-332-8093

Email: info@jagelectromagnetics.com

Saskatoon:

JAG Electromagnetics 30065-1624 33rd St. W Saskatoon, SK, S7L 7M6 Canada Tel (905)-635-7437 Fax (905)-332-8093

Email: info@jagelectromagnetics.com

Published by JAG and printed in Canada. This document cannot be printed or duplicated other than for its intended purpose as a JAG product selection guide without the written consent of JAG Electromagnetics.

Dated: February-15-2011

JAG-450-2-1/4-SM Product Specification Sheet.



Issue: 1

RF EMI Engineering Technology 26-1750 Creek Way Burlington, Ontario L7L 7E2 Canada

Email: info@jagelectromagnetics.com Web: www.jagelectromagnetics.com Tel (905)-635-7437 Fax (905)-332-8093 Made in Canada

Rev021511.1

Page 4/4



Copyright © JAG Electromagnetics

JAG's dedication to continuous Research & Development will result in product improvements as they evolve. Specifications are subject to change without notice. As a result, all information contained in the present datasheet is subject to confirmation at time of ordering